

LOW - VOLTAGE PENDANTS

Cone Pendant

DESCRIPTION

Case glass cone with reflective white interior or transparent glass cone. Case glass includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt replaceable 500 lumen 80 CRI 3000K LED SORAA® module. Transparent glass includes low-voltage, 50 watt MR16 flood lamp. Each include six feet of field-cutable suspension cable. Works with SORAA.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

ACCESSORIES & OPTICAL CONTROLS


SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook

WEIGHT

1.35lb / 0.61kg ±



cobalt



amber



cobalt



red



white

ORDERING INFORMATION

700	SYSTEM	CON	COLOR	FINISH	LAMP
FJ	FREEJACK		A AMBER	Z ANTIQUE BRONZE	12 VOLT HALOGEN
K	KABLE LITE		P COBALT	C CHROME	-LEDS830 12 VOLT LED 80 CRI 3000K
MP	MONOPOINT		R RED	S SATIN NICKEL	-24 24 VOLT HALOGEN
MO	MONORAIL		W WHITE		
MO2	TWO-CIRCUIT MONORAIL				

Note: Note: MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.

When installing LED option on MO2 only magnetic transformers may be used.

Chrome not offered on Monorail & Two~Circuit Monorail.



TECH LIGHTING®

7400 Linder Avenue
Skokie, Illinois 60077

T 847.410.4400
F 847.410.4500

Tech Lighting, L.L.C.

700 ____ CON ____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2017 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.