

# LOW - VOLTAGE PENDANTS

## Firefrit Pendant

### DESCRIPTION

A colorful twist on our popular Fire pendant with brilliant frit glass. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt, 300 delivered lumen, 3000K, replaceable SORAA® LED module and six feet of field-cutttable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on transformer). Works with SORAA.

### INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

### ACCESSORIES & OPTICAL CONTROLS


SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook

### WEIGHT

2lb / 0.91kg ±



tahoe pine amber



tahoe pine amber

white frit

### ORDERING INFORMATION

700	SYSTEM	FIRY	COLOR	FINISH	LAMP
	FJ	FREEJACK	A TAHOE PINE AMBER	Z ANTIQUE BRONZE	12 VOLT HALOGEN
	KL	KABLE LITE	W WHITE FRIT	C CHROME	-LEDS930 12 VOLT LED 90 CRI 3000K
	MP	MONOPOINT		S SATIN NICKEL	-24 24 VOLT HALOGEN
	MO	MONORAIL			
	MO2	TWO-CIRCUIT MONORAIL			

Note: Note: MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.

When installing LED option on MO2 only magnetic transformers may be used.

Chrome not offered on Monorail & Two~Circuit Monorail.

Chrome not offered on Monorail & Two~Circuit Monorail.



**TECH LIGHTING®**  
 7400 Linder Avenue T 847.410.4400  
 Skokie, Illinois 60077 F 847.410.4500  
**Tech Lighting, L.L.C.**

700 \_\_\_\_ FIRY \_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_