

LOW - VOLTAGE PENDANTS

Boreal Pendant

DESCRIPTION

Natural hemp fabric shade with recycled paper backing topped with recycled sand-cast bronze metal work. The fabric shade and recycled bronze are both sourced locally within 20 miles of our facility. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt, 300 delivered lumen, 3000K, replaceable SORAA® LED module and six feet of field-cutable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on transformer). Works with SORAA.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module

WEIGHT

2.0lb / 0.91kg ±



ivory



ORDERING INFORMATION

700	SYSTEM	BOR	COLOR	FINISH	LAMP
FJ	FREEJACK		I	Z ANTIQUE BRONZE	12 VOLT HALOGEN
KL	KABLE LITE			S WHITE BRONZE	-LEDS930 12 VOLT LED 90 CRI 3000K
MP	MONOPOINT				-24 24 VOLT HALOGEN
MO	MONORAIL				
MO2	TWO-CIRCUIT MONORAIL				

Note: While we feel they look very nice together, the boreal finishes will not be an exact match to existing satin nickel and antique bronze hardware.

MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.

Chrome not offered on Monorail & Two~Circuit Monorail.



TECH LIGHTING®
 7400 Linder Avenue T 847.410.4400
 Skokie, Illinois 60077 F 847.410.4500
Tech Lighting, L.L.C.

700 ____ BOR ____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____
