

# DISPLAY & EXHIBIT

## DJ-Wally Lite

---

### DESCRIPTION

Available in two lengths. Pivots at head to direct beam. 12 volt, MR16 lamp of up to 75 watts (not included). Chrome finish. See accessory for maximum wattage usage.

### INSTALLATION

Install a DisplayJack canopy or connector ports (sold separately) and push the DJ-Wally Lite's arms into the canopy or ports. After the show, pull out DJ-Wally Lite. The canopy or ports stay in place for next time with no need for an electrician.



### ACCESSORIES & OPTICAL CONTROLS

Backlight Shield, Barndoors, Cone Glass Shield, Lil Wok Shade, Round Glass Shield, Snap Louver Lens Holder

### WEIGHT

0.1lb / 0.05kg ±



dj-wally lite

### ORDERING INFORMATION

700DJWAL	LENGTH (A)	FINISH
	12 12" 24"	C CHROME



**TECH LIGHTING®**

7400 Linder Avenue  
Skokie, Illinois 60077

T 847.410.4400  
F 847.410.4500

**Tech Lighting, L.L.C.**

700DJWAL \_\_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_



©2018 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.