

# LOW - VOLTAGE PENDANTS

## Henrik Pendant

### DESCRIPTION

The Henrik pendant light from Tech Lighting features a spun metal upper body that is hand-painted with rubberized enamel for a soft, matte finish that is then combined with a beautifully hand-polished, premium pressed glass shade for a unique contemporary closed bottom LED pendant light. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt replaceable LED SORAA® module and six feet of field-cutttable cable. Works with SORAA.

### INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

### ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook

### WEIGHT

2.53lb / 1.15kg ±



black



black

brushed aluminum

white

### ORDERING INFORMATION

700 SYSTEM	HNK	COLOR	FINISH	LAMP
FJ	FREEJACK	B BLACK	S SATIN NICKEL	12 VOLT HALOGEN
MP	MONOPOINT	A BRUSHED ALUMINUM		-LEDS830 12 VOLT LED 80 CRI 3000K
MO	MONORAIL	W WHITE		-24 24 VOLT HALOGEN
MO2	TWO-CIRCUIT MONORAIL			

Note: MP includes 4" Round Flush Canopy.

When installing LED option on MO2 only magnetic transformers may be used.



7400 Linder Avenue T 847.410.4400  
Skokie, Illinois 60077 F 847.410.4500

Tech Lighting, L.L.C.

700 \_\_\_\_ HNK \_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_

\_\_\_\_\_

\_\_\_\_\_

