

# LOW - VOLTAGE PENDANTS

## Henrik Pendant SORAA

### DESCRIPTION

The Henrik pendant light from Tech Lighting features a spun metal upper body that is hand-painted with rubberized enamel for a soft, matte finish that is then combined with a beautifully hand-polished, premium pressed glass shade for a unique contemporary closed bottom LED pendant light. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt, 300 delivered lumen, 3000K, replaceable SORAA® LED module and six feet of field-cutable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on transformer). Works with SORAA.



black

### INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

### ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook

### WEIGHT

2.53-2.53lb / 1.15-1.15kg ±



black

brushed aluminum

white

### ORDERING INFORMATION

700	SYSTEM	HNK	COLOR	FINISH	LAMP
FJ	FREEJACK		B BLACK	S SATIN NICKEL	12 VOLT HALOGEN
MP	MONOPOINT		A BRUSHED ALUMINUM		-LEDS930 12 VOLT LED 90 CRI 3000K
MO	MONORAIL		W WHITE		-24 24 VOLT HALOGEN
MO2	TWO-CIRCUIT MONORAIL				

Note: MP includes 4" Round Flush Canopy.

When installing LED option on MO2 only magnetic transformers may be used.



**TECH LIGHTING®**  
 7400 Linder Avenue T 847.410.4400  
 Skokie, Illinois 60077 F 847.410.4500

**Tech Lighting, L.L.C.**

700 \_\_\_\_ HNK \_\_\_\_ \_\_\_\_

FIXTURE TYPE: \_\_\_\_\_

JOB NAME: \_\_\_\_\_

NOTES: \_\_\_\_\_  
 \_\_\_\_\_  
 \_\_\_\_\_