

Windsor Pendant



DESCRIPTION

The dual-tapered, elongated silhouette of the Windsor pendant light from Tech Lighting is inspired by men's neckties to create alluring dimension while the choice of hand painted metal or natural solid cast concrete offer varying texture options. Includes 50 watt halogen MR16 lamp or 6 watt, 435 delivered lumen, 3000K replaceable SORAA® MR16 LED lamp. Ships with six feet of field-cuttable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on the transformer). Works with SORAA.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system. For use on T~TRAK, order FreeJack version and T~TRAK FreeJack Connector (sold separately).

ACCESSORIES & OPTICAL CONTROLS

SORAA® LED Bi-Pin Replacement Pendant Module, Swag Hook



ORDERING INFORMATION

| 700 SYSTEM | WDS | COLOR | FINISH | LAMP | | | |
|------------|----------------------|-------|--------------|------|----------------|-----------------|--------------------------|
| FJ | FREEJACK | B | BLACK | Z | ANTIQUE BRONZE | 12 VOLT HALOGEN | |
| KL | KABLE LITE | C | CONCRETE | C | CHROME | -LED930 | 12 VOLT LED 90 CRI 3000K |
| MP | MONOPOINT | S | SATIN NICKEL | S | SATIN NICKEL | -24 | 24 VOLT HALOGEN |
| MO | MONORAIL | W | WHITE | | | | |
| MO2 | TWO-CIRCUIT MONORAIL | | | | | | |

Note: Note: MP includes 4" Round Flush Canopy.

Antique Bronze is not available for Kable Lite.



700 ____ WDS ____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____
