

LOW - VOLTAGE PENDANTS

Zenith Pendant SORAA

DESCRIPTION

Slender, organic-shaped glass with vertical stringers to add depth and dimension. Includes low-voltage, 50 watt halogen bi-pin lamp or 8 watt, 300 delivered lumen, 3000K, replaceable SORAA® LED module and six feet of field-cutable cable. Dimmable with low-voltage electronic or magnetic dimmer (based on the transformer). Works with SORAA.

INSTALLATION

Socket terminates with FreeJack male connector, which may be installed into a system connector. Elements ordered with a system prefix include a connector for that system.

ACCESSORIES & OPTICAL CONTROLS


SORAA® LED Bi-Pin Replacement Pendant Module

WEIGHT

2.02lb / 0.92kg ±



smoke



smoke large



smoke small



steel blue large



steel blue small



white large



white small

ORDERING INFORMATION

700	SYSTEM	ZEN	SHAPE OR SIZE	COLOR	FINISH	LAMP
FJ	FREEJACK		L LARGE	K SMOKE	Z ANTIQUE BRONZE	12 VOLT HALOGEN
MP	MONOPOINT		S SMALL	U STEEL BLUE	C CHROME	-LEDS930 12 VOLT LED 90 CRI 3000K
MO	MONORAIL			W WHITE	S SATIN NICKEL	-24 24 VOLT HALOGEN
MO2	TWO-CIRCUIT MONORAIL					

Note: MP includes 4" Round Flush Canopy. Note: MP includes 4 Round Flush Canopy.

Chrome not offered on Monorail & Two~Circuit Monorail.



TECH LIGHTING®

7400 Linder Avenue
Skokie, Illinois 60077

T 847.410.4400
F 847.410.4500

Tech Lighting, L.L.C.

700 ____ ZEN _____

FIXTURE TYPE: _____

JOB NAME: _____

NOTES: _____



©2017 Tech Lighting, L.L.C. All Rights Reserved. The "Tech Lighting" graphic is a registered trademark of Tech Lighting, L.L.C. Tech Lighting reserves the right to change specifications for product improvements without notification.