

BOREAL FREEJACK 4" ROUND FLUSH CANOPY



PRODUCT FEATURES



LAMPING

Mounts to a standard 4" junction box with round plaster ring (provided by electrician). Electronic transformer (included) fits in junction box. One FreeJack port; for ceiling or wall.

White Bronze



White Bronze

Antique Bronze

ORDERING INFORMATION

700FJ4RB	SHAPE OR SIZE	FINISH	VOLTAGE
	4" ROUND BOREAL INTEGRAL TRANSFORMER	Z ANTIQUE BRONZE	120V IN/12V OUT
		S WHITE BRONZE	024 120V IN/24V OUT
			277 277V IN/12V OUT

While we feel they look very nice together, the boreal finishes will not be an exact match to existing satin nickel and antique bronze hardware.

700FJ4RB _____

JOB NAME _____


NOTES _____



BOREAL FREEJACK 4" ROUND FLUSH CANOPY



SPECIFICATIONS



HARDWARE MATERIAL	
SHADE MATERIAL	
NET WEIGHT	
HEIGHT	
WIDTH	
LENGTH	
WET LISTED	
DAMP LISTED	
DRY LISTED	
SLOPED CEILING ADAPTABLE?	No
GENERAL LISTING	
INCLUDES	

LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS				
WATTS				
MAX WATTAGE PER BULB				
INPUT VOLTAGE				
DIMMING TYPE*				
CCT				
CRI				
LED LIFETIME				
L70				
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE				
LAMP SHAPE				
LAMP INCLUDED?				
WARRANTY**				

*Dimming information available at www.techlighting.com/Downloads#dimming
 ** Visit techlighting.com for specific warranty limitations and details.

T20 / T24 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6.			
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.			

* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

