

CASEN DRUM FLUSH MOUNT

PRODUCT FEATURES

- Features a sleek glass shade that's suspended from a handsome die-cast metal band
- Even generous light output free of hot spots and offensive glare
- Clear shade with a Satin Nickel finish
- Crafted by European glass artisans
- The LED Driver is housed within the junction box for this product
- 5 year warranty with LED lamping



LAMPING

Includes 15 watt, 1256 delivered lumen, 3000K LED module. Dimmable with most LED compatible ELV or Triac dimmers. 277V compatible with 0-10V dimmers.

Clear/Satin Nickel



Clear/Satin Nickel

Clear/Satin Nickel
OFF

Clear/Satin Nickel
ALT

ORDERING INFORMATION

700FMCASD COLOR	FINISH	LAMP
C CLEAR	S SATIN NICKEL	-LED830 LED 80 CRI 3000K 120V -LED830-277 LED 80 CRI 3000K 277V

700FMCASD _____

JOB NAME _____


NOTES _____



CASEN DRUM FLUSH MOUNT

SPECIFICATIONS

PRIMARY MATERIAL	Glass
SHADE MATERIAL	Glass
NET WEIGHT	5 lbs
HEIGHT	7.4in
WIDTH	7.3in
LENGTH	7.3in
UP LIGHT / DOWN LIGHT / BOTH?	
WET LISTED	
DAMP LISTED	
DRY LISTED	
WALL / CEILING MOUNT	
GENERAL LISTING	ETL Listed
INCLUDES	



LAMPING SPECIFICATIONS

	LED LAMP	INTEGRATED LED	NON LED	NO LAMP
DELIVERED LUMENS		1256		
WATTS		15		
MAX WATTAGE PER BULB		15W		
INPUT VOLTAGE/ DIMMING TYPE		120V ELV, TRIAC 277V 0-10V		
CCT		3000K		
CRI		90 CRI		
LED LIFETIME				
L70		>50000		
AVERAGE BULB HOURS				
FIELD SERVICEABLE LED				
LAMP BASE		Integrated LED		
LAMP SHAPE		Integrated LED		
LAMP INCLUDED?		True		
WARRANTY**		5 Years		

*Dimming information available at www.techlighting.com/Downloads#dimming
 ** Visit techlighting.com for specific warranty limitations and details.

T20 / T24 / JA8 INFORMATION

	Integrated LED	Replacement LED Lamp	No Lamp *
This product can be used to comply with California Building Energy Efficiency Standards 2016 Title 24 Part 6 / JA8.	No		
This product can be used to comply with California Appliance Efficiency Standards 2016 Title 20 and may be shipped to and sold in California.	N/A		

* If a light fixture or component does not include a lamp or light source, it is the responsibility of the customer to select a lamp that meets the T24 and T20 requirements.

